

Teams Rooms Accessories Compatibility Lists

TIP

- For a detailed introduction to each accessory and supported endpoints, please refer to [Meeting Room Endpoints Accessories](#).
- Enabling the host Wi-Fi may affect the use of the wireless content-sharing dongle and the wireless microphone. For more information, refer to [Can the Host Wi-Fi, Wireless Content Sharing Dongle, and the Wireless Microphone Be Enabled Simultaneously?](#)

MeetingBar Compatibility

NOTE

- Different versions of the VCR20 cannot be mixed between MTRoW and MTRoA systems.
- The microphones of different models in the list cannot be mixed; however, the VCM36-W is an expansion microphone that can be used with the built-in microphone.

Item	MeetingBar A10	MeetingBar A20	MeetingBar A30	MeetingBar A25	MeetingBar A40	MeetingBar A50
WPP20	×	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing	×	×	×
WPP30	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing	√ - Support pairing up to 4 but only using 1 at a time - Support content sharing and IP-BYOD (A40 version requires 289.320.0.70 and later)	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing and IP-BYOD (A40 version requires 289.320.0.70 and later)	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing and IP-BYOD
PA20	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing and IP-BYOD (A10 version requires 278.320.0.77 and later)	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing only (A20 version requires 133.320.0.135 and later)	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing only (A30 version requires 133.320.0.135 and later)	√ - Support pairing up to 4 but only using 1 at a time - Support content sharing and IP-BYOD	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing and IP-BYOD (A40 version requires 289.320.0.60 and later)	√ - Support pairing up to 4, but only using 1 at a time - Support content sharing and IP-BYOD
VCH51	√ - Support pairing/using up to 1 - Support content sharing and BYOD (A10 version requires 278.320.0.77 and later)	√ - Support pairing/using up to 1 - Support content sharing and BYOD	√ - Support pairing/using up to 1 - Support content sharing and BYOD	√ - Support pairing/using up to 1 - Support content sharing and BYOD	√ - Support pairing/using up to 1 - Support content sharing and BYOD (A40 version requires 289.320.0.43 and later)	√ - Support pairing/using up to 1 - Support content sharing and BYOD
VCH51 Pro	√ - Support pairing/using up to 1 - Support content sharing and BYOD	×	×	√ - Support pairing/using up to 1 - Support content sharing and BYOD (A25 version requires 346.320.0.22 and later)	√ - Support pairing/using up to 1 - Support content sharing and BYOD	√ - Support pairing/using up to 1 - Support content sharing and BYOD
VCM34	×	√ - Support pairing/using up to 2 VCM34 is used as an external microphone	√ - Support pairing/using up to 3 VCM34 is used as an external microphone	×	×	×

VCM35	✓ - Support pairing/using up to 1 VCM35 is used as an expansion microphone (A10 version requires 278.320.0.77 and later)	✓ Support pairing/using up to 2 VCM35 is used as an external microphone (A20 version requires 133.320.0.18 and later)	✓ Support pairing/using up to 3 VCM35 is used as an external microphone (A30 version requires 133.320.0.18 and later)	×	✓ - Support pairing/using up to 2 VCM35 is used as an expansion microphone	✓ - Support pairing/using up to 3 VCM35 is used as an expansion microphone
VCM36-W	×	✓ - Support pairing/using up to 1 VCM36-W is used as an expansion microphone. (A20 version requires 133.320.0.135 and later)	✓ - Support pairing/using up to 2 VCM36-W is used as an expansion microphone. (A30 version requires 133.320.0.135 and later)	×	✓ - Support pairing/using up to 2 VCM36-W is used as an expansion microphone.	✓ - Support pairing/using up to 3 VCM36-W is used as an expansion microphone.
VCM38	×	✓ - Support pairing/using up to 2 VCM38 is used as an external microphone (A20 version requires 133.310.0.25 and later)	✓ - Support pairing/using up to 3 VCM38 is used as an external microphone (A30 version requires 133.310.0.25 and later)	×	×	×
CPW65	×	×	×	×	×	×
CPW90-BT	×	×	×	×	×	×
CPW90	×	✓ - Support pairing/using up to 1 pair, that is, 2 CPW90 devices CPW90 is used as an external microphone (A20 version requires 133.310.0.25 and later)	✓ - Support pairing/using up to 1 pair, that is, 2 CPW90 devices CPW90 is used as an external microphone (A30 version requires 133.310.0.25 and later)	×	×	×
CM20	×	✓ - Support pairing/using up to 2 CM20 is used as an external microphone (A20 version requires 133.320.0.135 and later)	✓ - Support pairing/using up to 2 CM20 is used as an external microphone (A30 version requires 133.320.0.135 and later)	×	✓ - Support pairing/using up to 2 CM20 is used as an external microphone (A40 version requires 289.320.0.31 and later)	✓ - Support pairing/using up to 3 CM20 is used as an external microphone
CS10	×	✓ Support pairing/using up to 2 Only work with CM20 (A20 version requires 133.320.0.135 and later)	✓ - Support pairing/using up to 2 Only work with CM20 (A30 version requires 133.320.0.135 and later)	×	✓ - Support pairing/using up to 2 Only work with CM20 (A40 version requires 289.320.0.31 and later)	✓ Support pairing/using up to 3 Only work with CM20
CM50	×	×	×	×	×	✓ The maximum number of supported CM50 depends on the capability of the AP08 or AVBridge Work with CS10-D CM50 is used as an external microphone
CS10-D	×	×	×	×	×	✓ The maximum number of supported CS10-D depends on the capability of the AP08 or AVBridge Only work with CM50
MTower	×	×	×	×	✓ A40 version requires 289.320.0.70 and later	✓ A50 version requires 322.320.0.42 and later (Coming soon)
MSpeaker II	×	×	×	×	×	×
MSpeech	×	×	×	×	×	×
UVC30	×	×	×	×	×	✓ UVC30 is used as a content camera
UVC34	×	×	×	×	×	×
UVC40	×	×	×	×	×	×
UVC40 E2	×	×	×	×	×	×

UVC84/UVC86	×	×	×	×	×	×
UVC85	×	×	×	×	×	×
MB-CAM-6X/MB-CAM-12X	×	×	×	×	×	×
CTP18	✓ Support pairing/using up to 1	✓ Support pairing/using up to 1	✓ Support pairing/using up to 1	×	×	×
CTP25	×	×	×	✓ Support pairing/using up to 1 Support content sharing and BYOD	✓ Support pairing/using up to 1 Support content sharing and BYOD	✓ Support pairing/using up to 1 Support content sharing and BYOD
MTouch II/MTouch Plus/MTouch E2	×	×	×	×	×	×
VCR11	✓	✓	✓	✓	✓	✓
VCR20 [1]	×	✓	✓	×	×	×
MeetingDisplay	×	×	×	✓	✓	✓
AVBridge	×	×	×	×	✓ A40 version requires 289.320.0.70 and later	✓ A50 version requires 323.320.0.34 and later
AP08	×	×	×	×	✓ A40 version requires 289.320.0.70 and later	✓ A50 version requires 323.320.0.34 and later

Yealink MeetingBoard Compatibility

NOTE

- The VCM35/VCM36-W is used as an expansion microphone.

Item	MeetingBoard	MeetingBoard Pro	MeetingBoard C	MeetingBoard Pro + MCore OPS-T
WPP20	Support pairing up to 4, using 1 at a time.	×	×	×
WPP30	Support pairing up to 4, using 1 at a time. (MeetingBoard 65&86 version requires 155.15.0.37 and later)	Support pairing up to 4, using 1 at a time	Support pairing up to 4, using 1 at a time	Support pairing up to 4, using 1 at a time
PA20	Support pairing up to 4 but only using 1 at a time. (MeetingBoard 65&86 version requires 155.15.0.117 and later)	Support pairing up to 4 but only using 1 at a time.	Support pairing up to 4 but only using 1 at a time	Support pairing up to 4 but only using 1 at a time
VCH51	Supports wired screen sharing, wired BYOD, and reverse control (BYOD) - The reverse control feature requires MeetingBoard version 155.15.0.117 or later.	Supports wired screen sharing, wired BYOD, and reverse control (BYOD)	Supports wired screen sharing, wired BYOD, and reverse control (BYOD)	Supports wired screen sharing, wired BYOD, and reverse control (BYOD)
VCH51 Pro	×	Supports wired screen sharing, wired BYOD, and reverse control (BYOD)	×	✓ (Coming soon) Supports wired screen sharing, wired BYOD, and reverse control (BYOD)
VCM34	×	×	×	×
VCM35	Support pairing/using up to 2 (MeetingBoard 65&86 version requires 155.15.0.46 and later)	Support pairing/using up to 4	Support pairing/using up to 2	Support pairing/using up to 4
VCM36-W	Support pairing/using up to 2 (MeetingBoard 65&86 version requires 155.15.0.46 and later)	Support pairing/using up to 4	Support pairing/using up to 1	Support pairing/using up to 4
VCM38	×	×	×	×
CPW90-BT	×	×	×	×
CPW90	×	×	×	×
CPW65	×	×	×	×

CM20+CS10	- Supports up to 4 CM20 paired with 4 CS10 speaker - Supports up to 4 CM20 using the built-in speaker - (MeetingBoard 65&86 version requires 155.15.0.117 and later)	- Supports up to 4 CM20 paired with 4 CS10 speaker - Supports up to 4 CM20 using the built-in speaker	×	- Supports up to 4 CM20 paired with 4 CS10 speaker - Supports up to 4 CM20 using the built-in speaker
CM50+CS10 -D+AP08	×	✓ The maximum number of supported CM50 and CS10-D depends on the capability of the AP08.	×	✓ The maximum number of supported CM50 and CS10-D depends on the capability of the AP08.
MSpeaker II	×	×	×	×
MSpeech	×	×	×	×
UVC30	×	×	×	×
UVC84 or UVC86	- Supports up to 3 simultaneous connections. - Only one camera can be used at a time. - Multi-camera stitching not supported.	- Supports up to 3 simultaneous connections. - Only one camera can be used at a time - Multi-camera stitching not supported.	- Supports up to 3 simultaneous connections(via the VCH port). - Only one camera can be used at a time - Multi-camera stitching not supported.	- Supports up to 3 simultaneous connections(via the VCH port). - Only one camera can be used at a time - Multi-camera stitching not supported.
MTower	×	Coming soon	×	Coming soon
MB-CAM- 6X/12X	- MB-CAM-6X: MeetingBoard 65&86 version requires 155.15.0.37 and later. - MB-CAM-12X: MeetingBoard 65&86 version requires 155.15.0.46 and later	×	×	×
MB- 12X Pro	×	✓	×	✓
MCore-OPS	✓ (MeetingBoard 65&86 version requires 155.15.0.37 and later)	✓	×	-
MCore-OPS- T	✓	✓	×	-
CTP18	✓ - On the Teams platform, only one CTP18 is supported. - On Zoom and in general mode (BYOM), up to four can be supported. (MeetingBoard 65&86 version requires 155.15.0.37 and later)	×	×	×
CTP25	×	✓	Coming soon	×
ETV65&86	✓ Support pairing/using up to 1 (MeetingBoard 65&86 version requires 155.15.0.46 and later)	×	×	×
AVHUB	×	Coming soon	×	Coming soon
MTouch II/E2	×	×	×	
MTouch Plus-MB	×	×	×	Coming soon
MTouch Plus	×	×	×	×
VCR11	×	×	×	×
VCR20	×	×	×	×
MB-Remote	✓	✓	✓	×

Yealink MeetingDisplay Compatibility

Item	MeetingDisplay
WPP20	×
WPP30	Support pairing up to 4, using 1 at a time. (Only for content sharing)
PA20	Support pairing up to 4, using 1 at a time. (Only for content sharing)
VCH51	×
VCH51 Pro	×
VCM34	×
VCM35	×

VCM36-W	×
VCM38	×
CPW90-BT	×
CPW90	×
CPW65	×
CP50	×
CPE40	×
CM20+CS10	×
CM50+CS10-D+AP08	×
MSpeaker Pro	√
MSpeech	×
MB-12X Pro	×
MCore-OPS-T	×
CTP18	×
CTP25	×
AVHUB	×
MTouch II/Plus/E2	×
VCR11	×
VCR20	×
MB-Remote	√

NOTE

MeetingDisplay supports various collaboration features when integrated with MTR devices.
The following MTR models are supported

Category	Item	MeetingDisplay
MeetingBar	MeetingBar A40	√
	MeetingBar A50	√
MVC Series	MVC S80-C5U-000 / ZVC S80-C5U-000	√
	MVC S40-C4U-000	√
	MVC S40-C5U-000 / ZVC S40-C5U-000	√
	MVC S40 Plus-C5U-000	√
	MVC S50-C5U-000 / ZVC S50-C5U-000	√
	MVC 860-C5U-000 / ZVC 860-C5U-000	√

MVC (MTR) Compatibility

Important Notes

Limitations on Additional Camera and Microphone

- MVC Kits with AVHub**
 - Supports up to **9 UVC cameras**.
 - Refer to the next section "**Limitations on Yealink AVHub with UVC Cameras**" for details.
- MVC Kits without AVHub**
 - Multiple UVC cameras can connect to the USB port of the Yealink mini-PC simultaneously.
 - However, only **1 UVC camera** can be used at a time.

Limitations on Yealink AVHub with UVC Cameras

- Direct Connection to AVHub (75W):**
 - Maximum of **2 UVC86 (30W)** or **4 UVC84 (20W) cameras** can be connected.
 - Exceeding this limit requires using a PoE+ switch compliant with the **802.3 AT (PoE+) standard**.
- Using a PoE+ Switch with AVHub:**
 - Supports up to **9 UVC84/UVC86 cameras** when connected via a compliant PoE+ switch.

Limitations on Yealink AVHub with CS10/CM20

- Compatibility with Microphones:**
 - Supports the **CM20**, **VCM38**, and **VCM35** microphones (one type only; mixing models is not supported).

2. Direct Connection to AVHub (75W):

- Maximum: **4 CS10 (24W)** and **4 CM20 (9W)** microphones due to PoE power budget limitations.

3. Extending Connectivity with PoE+ Switch:

- Use a PoE+ switch to connect more peripherals. Refer to the next section **"Connecting CM20/CS10 via a PoE+ Switch"** for details.

Connecting CM20/CS10 via a PoE+ Switch

- Ensure the switch is a **Gigabit Ethernet switch** with the **EEE (Energy-Efficient Ethernet)** feature **disabled** (if the feature exists).
 - Example: The **EEE feature of RCH40 cannot be disabled**, so it is incompatible with CM20/CS10.
- Power supply limitations:
 - A single **RCH40 E2 (90W)** supports:
 - 2 CM20 (9W) + 2 CS10 (24W)**, or
 - 3 CS10s (24W) only**.
 - Connecting **4 CS10s (24W) simultaneously** is not recommended due to insufficient power.

External Microphone Compatibility with MVC Devices

- Supported microphones:
 - Yealink Array Microphone (VCM)**
 - Yealink DECT Wireless Microphone (CPW)**
 - Yealink Ceiling Microphone (CM)**
- MVC S40 Specifics:**
 - Support **VCM35/VCM36-W** as expansion microphones alongside the built-in microphone.
 - Support **CM20** as an external microphone but cannot operate with the built-in microphone simultaneously.

Connecting CM20/CS10 with UVC84/UVC86 (without AVHub)

- CS10** is compatible with **CM20**.
- CM20** works with **CS10** and **MSpeaker II**.

Microphone Priority for MVC Devices

MVC devices do not support audio mixing for connected microphones. The audio input device with the highest priority will be used in the following order: **CM20 > VCM38 > VCM35 > VCM34 > VCM36-W > CPW90/CPW90-BT > CPW65 > Line-In > Built-in microphone > USB to Line-In**.

Yealink AVHub and Cameras Compatibility

Item	MeetingBar A50 USB Mode	SmartVisio n 80	SmartVisio n 60	SmartVisio n 40	AVHub	UVC86	UVC84	UVC40 E2	UVC40	UVC34	UVC30
VCH51	×	×	×	√ (SmartVisio n 40 version requires 286.413.0.30 and later)	×	×	×	×	×	×	×
VCH51 Pro	×	×	×	×	×	×	×	×	×	×	×
VCM34	×	×	×	×	Support pairing/using up to 8 at a time	Support pairing/using up to 6 at a time	Support pairing/using up to 6 at a time	×	Support pairing/using up to 2 at a time	×	×
VCM35	Support pairing/using up to 3 at a time	Support pairing/using up to 8 at a time	×	Support pairing/using up to 2 at a time	Support pairing/using up to 8 at a time (AVHub version requires 153.431.0.5 and later)	Support pairing/using up to 8 at a time (UVC86 version requires 151.431.0.5 and later)	Support pairing/using up to 8 at a time (UVC84 version requires 262.431.0.5 and later)	Support pairing/using up to 1 at a time	×	×	×
VCM36-W	Support pairing/using up to 3 at a time	Support pairing/using up to 4 at a time (SmartVisio n 80 version requires 321.435.0.70 and later)	×	Support pairing/using up to 2 at a time	Support pairing/using up to 4 at a time (But the stability will be affected when AVHub is deployed inside the cabinet).	Support pairing/using up to 4 at a time (UVC86 version requires 151.431.0.5 and later)	Support pairing/using up to 2 at a time (UVC84 version requires 262.431.0.5 and later)	Support pairing/using up to 1 at a time	×	×	×
VCM38	×	×	×	×	Support pairing/using up to 8 at a time	Support pairing/using up to 8 at a time	Support pairing/using up to 8 at a time	×	Support pairing/using up to 2 at a time	×	×

CPW90-BT	×	×	×	×	×	×	×	×	×	×	×
CPW90	×	×	×	×	Support pairing/using up to 2 pair, i.e., 4 at a time	Support pairing/using up to 2 pair, i.e., 4 at a time	Support pairing/using up to 1 pair, i.e., 2 at a time	×	Support pairing/using up to 1 pair, i.e., 2 at a time	×	×
CPW65	×	×	×	×	Support pairing/using up to 1 pair, i.e., 2 (AVHub version requires 153.431.0.5 and later)	Support pairing/using up to 1 pair, i.e., 2 (UVC86 version requires 151.431.0.5 and later)	Support pairing/using up to 1 pair, i.e., 2 (UVC84 version requires 262.431.0.5 and later)	×	×	×	×
CM20	3 (Work with CS10 or built-in speaker)	Support pairing/using up to 4 at a time	×	Support pairing/using up to 2 at a time	Support pairing/using up to 4 (AVHub version requires 153.435.0.3 5 and later)	Support pairing/using up to 4 (UVC86 version requires 151.433.0.1 5 and later)	Support pairing/using up to 4 (Connect to UVC84 and its version requires 262.433.0.1 0 and later). The Line Out port of the UVC84 will become unavailable .	×	×	×	×
CS10	3 (Only work with CM20)	Support pairing/using up to 4 at a time (Only work with CM20)	×	Support pairing/using up to 2 at a time Only work with CM20	Support pairing/using up to 4 (AVHub version requires 153.435.0.3 5 and later)	Support pairing/using up to 4 (Connect to UVC86 and its version requires 151.433.0.1 5 and later) Only work with CM20	Support pairing/using up to 4 (Connect to UVC84 and its version requires 262.433.0.1 0 and later) Only work with CM20	×	×	×	×
MTower	✓	×	×	✓	×	×	×	×	×	×	×
MSpeaker II	×	Support pairing/using up to 4 at a time	×	×	Support pairing/using up to 4 at a time	Support pairing/using up to 4 at a time	Support pairing/using up to 4 at a time	×	×	×	×
MSpeaker Pro	×	Support pairing/using up to 4 at a timeSupport pairing/using up to 4 at a time	×	×	Support pairing/using up to 4 at a time	Support pairing/using up to 4 at a time	×	×	×	×	×
MVC-BYOD-EXtender (Only work with MTR bundle)	✓	✓	×	✓	✓	✓	✓	×	✓	×	×
USB Connector	✓	✓	×	✓	✓	✓	✓	✓	✓	✓	✓
VCR11	✓	×	×	×	×	×	×	×	×	×	×
VCR20 [1]	×	✓	×	✓	✓	✓	✓	✓	✓	✓	✓

NOTE

[1] Different versions of the VCR20 remote control can control different devices. For more information, please refer to [VCR20 Remote Control Compatibility](#).

Yealink MTouch Touch Panel Compatibility

	MTouch II	MTouch E2	MTouch Plus
WPP20	✓	×	×
WPP30	×	✓ (Support pairing up to 8, connecting 4 but only using 1 at a time)	✓ (Support pairing up to 8, connecting 4 but only using 1 at a time)
PA20	×	✓ (Support pairing up to 8, connecting 4 but only using 1 at a time)	✓ (Support pairing up to 8, connecting 4 but only using 1 at a time)
RoomSensor	×	×	✓

Yealink mini-PC Compatibility

	MCore	MCore Pro	MCore Lite	MCore 4
UVC30 Content Camera	✓	✓	✓	✓
MSpeech	✓ (Support pairing/using 1 at a time)	✓ (Support pairing/using 1 at a time)	✓ (Support pairing/using 1 at a time)	✓ (Support pairing/using 1 at a time)
CTP25	×	×	×	✓

Pro Audio Compatibility

Item	AVBridge	AP08
VCM34	×	×
VCM35	×	×
VCM36-W	×	×
VCM38	×	×
CPW90-BT	×	×
CPW90	×	×
CPW65	×	×
CP50	×	×
CPE40	×	×
CM20	4 (CM20 version requires 294.435.0.25 and later)	8(CM20 version requires 294.435.0.25 and later)
CM50	1 (CM50 version requires 294.435.0.25 and later)	8(CM50 version requires 294.435.0.25 and later)
CS10	20 (CS10 version requires 298.435.0.20 and later)	20 (CS10 version requires 298.435.0.20 and later)
CS10-D	20 (CS10-D version requires 298.435.0.20 and later)	20 (CS10-D version requires 298.435.0.20 and later)
AP08	✓ (AP08 version requires 294.435.0.25 and later)	/
AVBridge	/	✓ (AVBridge version requires 340.435.0.35 and later)
MSpeaker II	×	×
MSpeaker Pro	8 (MSpeaker Pro version requires 341.435.0.50 and later)	8 (MSpeaker Pro version requires 341.435.0.50 and later)
MSpeech	×	×
UVC30	×	×
UVC34	×	×
UVC40	×	×
UVC40 E2	×	×
UVC84	×	×
UVC86	✓ (UVC86 version requires 151.435.0.40 and later)	×
MeetingBar A50 USB Mode	✓ (A50 version requires 322.320.0.45 and later)	✓ (A50 version requires 322.320.0.45 and later)
SmartVision 40	×	×
SmartVision 60	×	×
SmartVision 80	✓ (SmartVision 80 version requires 321.435.0.65 and later)	×
AVHub	✓ (AVHub version requires 153.435.0.50 and later)	✓ (AVHub version requires 153.435.0.50 and later)
MeetingBar A10	×	×
MeetingBar A20	×	×
MeetingBar A30	×	×
MeetingBar A40	✓ (A40 version requires 289.320.0.70 and later)	✓ (A40 version requires 289.320.0.70 and later)
MeetingBar A50	✓ (A50 version requires 323.320.0.34 and later)	✓ (A50 version requires 323.320.0.34 and later)

MeetingBoard 65&86	×	×
MeetingBoard Pro + MCore OPS-T	√	√
MeetingBoard Pro	√ (MeetingBoard Pro version requires 331.320.0.30 and later)	√ (MeetingBoard Pro version requires 331.320.0.30 and later)
MeetingDisplay	×	×
MeetingEye 500	×	×
Yealink Room Designer	√ (Designer version requires 26.35.0.10 and later)	√ (Designer version requires 26.35.0.10 and later)
Yealink RoomConnect	√ (YRC version requires 2.35.183.0 and later)	√ (YRC version requires 2.35.183.0 and later)
Third-Party Dante or Analog Microphone	√	√
Third-Party Dante or Analog Speaker	√	√
CTP18	×	×
CTP25	√	√
MTouch II	×	×
MTouch Plus	√	√
MTouch E2	×	×
MCore	√	√
MCore Pro	√	√
MCore Lite	√	√
MCore 4	√	√
RoomSensor	√	√
RoomSensor Pro	×	×
YPS20	×	√

NOTE

1. Due to the upgrade of the device network architecture, the older version devices cannot use one-click deployment or be configured via Designer when paired with AVBridge. Please ensure that both the device and software versions are upgraded to the specified version or higher before use.
2. The AVBridge/AP08 output port and speakers previously used multicast communication, which is theoretically unlimited in quantity. The numbers listed in the above table represent the stable quantities tested and verified by Yealink.

DeskVision A24 Compatibility

Wireless keyboard and mouse:

Brand	Model
Logitech	K380
	K580
	K780
	MK270
Surface Keyboard	Holgate
	Surface Keyboard
HP	CS750
lenovo	LBK500
	S6000
PHILIPS	SPK6614
RAPOO	× K100
Acer	LK-416B
Apple	Magic Keyboard & Magic Mouse

Headsets:

Brand	Model	Connection Type
Yealink	UH34/UH36/UH37/UH38	USB
	WH62/WH63/WH66/WH67	
Poly	Blackwire 3220	
	Blackwire 3310	
	Blackwire 5220	
Jabra	Jabra Evolve 20	
	Jabra Evolve 40	

	Engage 65 Stereo & Mono	Bluetooth
	Engage 75 Stereo & Mono	
Yealink	BH71/BH72/BH76	
Poly	Voyager 4320	
	Voyager Focus2 UC	
	Voyager Focus	
	VOYAGER 5200	
	Legend	
Jabra	Evolve 65	
	Evolve 75	
	Evolve2 65	
	Evolve2 75	
Apple	AirPods	
	AirPods Pro	

FAQ

Can the built-in microphone and external microphone pick up sound at the same time?

Does the MeetingBar A×0 support the simultaneous use of multiple microphone devices?

Can the host Wi-Fi, wireless content sharing dongle, and the wireless microphone be enabled simultaneously?

When the host Wi-Fi, wireless content sharing dongle, and the wireless microphone are simultaneously enabled, the compatibility is as follows:

Wireless Content Sharing Dongle is used	A10	A20	A30	A25	A40	A50	MeetingBoard	MeetingBoard Pro
Wireless Microphone	×	√	×	×	√	√	√	√
Host Wi-Fi	×	×	×	×	√	√	√	√
Host Wi-Fi is enabled	A10	A20	A30	A25	A40	A50	MeetingBoard	MeetingBoard Pro
Wireless Microphone	×	×	×	×	√	√	√	√
Wireless Content Sharing Dongle	×	×	×	×	√	√	√	√
Wireless Microphone is used	A10 (NA)	A20	A30	A25 (NA)	A40	A50	MeetingBoard	MeetingBoard Pro
Host Wi-Fi	×	×	×	×	√	√	√	√
Wireless Content Sharing Dongle	√	√	√	√	√	√	√	√